

Suiteplex Suite Unit 3806

General Information

The Model 3806 SUITE UNIT is a 6-zone, home-run wired, subscriber's control panel. This panel must be used in conjunction with the model 3850 concierge control panel. The suite unit has 3 arming modes (HOME, SLEEP, FULL) to allow for partial arming of a suite unit, as well as full arming. In addition, each suite unit can have up to 5 permanent user codes.



Specifications

- * 6-zone, home-run wires loops.
- * 4 of these loops use a 2-wire circuit, either normally closed or double EOL.
- * The other 2 loops use a 2-wire, single EOL circuit.
- * 20-character, 2-line, backlit LCD display.
- * 20-button, tactile-operation keypad.
- * 5 user codes.
- * User codes are programmable from the suite unit.
- * Single-press FIRE, PANIC, MEDICAL buttons.
- * User-selectable door chime.
- * User-selectable zone bypass.

Enclosure

- * ABS plastic, available in white only.
 - * Dimensions: 5 3/4"W x 4 1/2"H x 1 1/2"D.
- Weight 1/2lb.

Outputs

- * .015 amps at 12 VDC (back-light off).
- * .05 amps at 12 VDC (back-light on).

SUITEPLEX SUITE UNIT 3806

PRODUCT
CODE
3806

Suiteplex Suite Unit 3806ZL

General Information

The Model 3806ZL SUITE UNIT is a 6-zone, home-run wired, subscriber's control panel. This panel must be used in conjunction with the model 3850 concierge control panel. The suite unit has 3 arming modes (HOME, SLEEP, FULL) to allow for partial arming of a suite unit, as well as full arming. In addition, each suite unit can have up to 5 permanent user codes.



Specifications

- * 6-zone, home-run wires loops.
- * 4 of these loops use a 2-wire circuit, either normally closed or double EOL.
- * The other 2 loops use a 2-wire, single EOL circuit.
- * 20 zone status LEDs in rectangular window.
- * 20-button, tactile-operation keypad.
- * 5 user codes.
- * Single-press FIRE, PANIC, MEDICAL buttons.
- * User-selectable door chime.
- * User-selectable zone bypass.

Enclosure

- * ABS plastic, available in white only.
- * Dimensions: 5 3/4"W x 4 1/2"H x 1 1/2"D.
- * Weight 1/2lb.

Outputs

- * .02 amps at 12 VDC (all zone LEDs on).